




Small Appliance Module

For use with plug-in TV, electronics and lighting

Model HA-02WD
Operating Instructions
and Owner's Manual



This product is compatible with other Z-Wave™ enabled products

IMPORTANT NOTICE!

Read the enclosed instructions carefully before installing the Model HA-02WD Electronics Module. Pay close attention to all instruction steps and notes. This manual should be retained for future reference.

Table of contents


Package Contents	2
Introduction	2-3
Installation	4
Operation	5-6
Programming	7
Specifications	7
Compliance.....	8

1

Package Contents



Model HA-02WD
Small Appliance Module



Instruction
Manual

Introduction

Thank you for purchasing the HA-02WD HomeSettings Small Appliance Module. HomeSettings products by Wayne-Dalton allow you *to control your home by remote control*. You can create a complete Home Control and Access Network by combining your Small Appliance Module with other HomeSettings products. Indoor and outdoor lighting, TVs, garage door openers, and thermostats are just a few of the items you can easily control with additional HomeSettings products.

Introduction continued:



Your new Small Appliance Module is compatible with the complete range of Z-Wave™ enabled HomeSettings products. Furthermore, other Z-Wave™ enabled controllers regardless of brand will also work with your Small Appliance Module. Please consult with your controller supplier for more details.

Home Control Basics:

HomeSettings products allow you to easily control multiple devices in a home with the push of a button in what is known as a “scene”. Turning on all of the lights as you come home is an example of a scene. Dimming lights and closing your curtains to watch TV, it’s also a scene.

Visit www.wayne-dalton.com/access to get ideas on how to create scenes with your Small Appliance Module and other Z-Wave™ enabled HomeSettings products.


3

1 Installation	
<p>1. Plug the HA-02WD Small Appliance Module into a 120VAC, 60Hz outlet.</p>	 <p>PLUG UNIT INTO OUTLET</p>
<p>2. Plug a lamp, appliance, or other electronic device into the module.</p>	
<p>3. Turn the knob or switch on the lamp, appliance, or other electronic device to the ON position.</p>	

2 Manual Operation

4. To manually turn ON the HA-02WD Small Appliance Module, press and release the Program/ON/OFF button. The green indicator LED will turn ON, and the lamp, appliance or other electronics module plugged into the HA-02WD Small Appliance Module will also turn ON.

PROGRAM ON/OFF BUTTON



GREEN LED INDICATOR

3 Manual Operation (cont.)

5. To manually turn OFF the HA-02WD Small Appliance Module, simply press and release the Program/ON/OFF button. The green indicator will turn OFF and the lamp, appliance or other electronic device plugged into the HA-02WD Small Appliance module will also turn OFF.

Note: If the device does not turn ON, confirm the power switch for your device is turned to the "ON" position.

PROGRAM ON/OFF BUTTON



GREEN LED INDICATOR

4 Programming	
Refer to the instructions for the HA-07WD Deluxe Remote Control, HA-09WD Remote Control, or WDHA-12R Gateway Module for programming this device.	

5 Specifications	
For Home or Office Use in Dry Locations Only Ratings: 15 Amperes Resistive 8.3 Amperes Tungsten 42 Watts Compact Fluorescent 120VAC, 60 Hz Operating Temperature Range: 0° C to 40° C Made In China	

7

FCC and IC Statement

FCC Regulatory Information:

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try and correct the interference by one or more of the following measures:

- reorient or relocate the receiving antenna,
- increase the separation between the equipment and receiver,
- connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

IC Regulatory Information:

This Class B digital apparatus meets all requirements of the Canadian Interference Causing Equipment Regulations. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation of the device.

Cet appareillage numérique de la classe B répond a toutes les exigences de l'interférence canadienne causant des règlements d'équipement. L'opération est sujette aux deux conditions suivantes: (1) ce dispositif peut ne pas causer l'interférence nocive, et (2) ce dispositif doit accepter n'importe quelle interférence reçue, y compris l'interférence qui peut causer l'opération peu désirée.

WARNING: Changes or modifications to this receiver not expressly approved by Wayne-Dalton Corp. could void the user's authority to operate this equipment.